arXiv:1203.5395v2 [cs.IT] 9 Sep 2012

Data Dissemination in Wireless Networks with Network Coding

Mohammad H. Firooz, *Student Member, IEEE,* Sumit Roy *Fellow, IEEE,*
Electrical Engineering Department
University of Washington
Seattle, WA 98105.
{firooz,sroy}@u.washington.edu

Abstract

We investigate the use of network coding for information dissemination over a wireless network. Using network coding allows for a simple, distributed and robust algorithm where nodes do not need any information from their neighbors. In this paper, we analyze the time needed to diffuse information throughout a network when network coding is implemented at all nodes. We then provide an upper bound for the dissemination time for ad-hoc networks with general topology. Moreover, we derive a relation between dissemination time and the size of the wireless network. It is shown that for a wireless network with N nodes, the dissemination latency is between $O(N)$ and $O(N^2)$, depending on the reception probabilities of the nodes. These observations are validated by the simulation results.

I. INTRODUCTION

The information dissemination problem, at its root, is a classical broadcast problem: sharing data residing at one node (source) with all others (destinations) in the network. The significance of this problem can be readily gauged by the extensive history of prior work on this topic, which has contributed to the design of networked communications with protocol stacks that support efficient broadcasting.

Of late, a more modern version of the one-to-many (broadcast) problem has gained prominence; this is typically referred to as a *data sharing* among multiple peer-to-peer (p2p) nodes, or the *all-to-all* problem. This problem arises when each node in a network obtains only *a* *fraction of the total information* (e.g. part of a video-on-demand file or a software update) desired collectively by all. In a simplified version of the all-to-all data-dissemination problem, a source file desired by all, is divided into N mutually exclusive *information packets*, and each packet is stored at exactly one node in the network [1], [2]. Every node wishes to acquire the remaining $N-1$ pieces of the source file; the order in which each node receives the remaining information packets is not relevant.

Traditionally, the data dissemination problem over a decentralized network architecture has focussed on the impact of the *dissemination algorithm* designed to optimize a performance metric such as the dissemination latency, i.e., the time required for *all nodes* to acquire the entire file [3]. Our contribution in this paper is to analyze the impact of network coding to this problem. One of the most significant benefits of our approach is that nodes do *not* need extra information from other nodes regarding the state of the network [4] to accomplish dissemination, significantly reducing communication overhead.

The prior analytical models used for this problem have largely suffered from unrealistic assumptions that are unsuited to a wireless network - notably that of pure fail/success $(0-1)$ whereby either each transmission is either successfully received by *all* neighbors or fails. Our analysis advances the state of the art by using a more appropriate link model whereby for each broadcast, sink nodes successfully receive the transmitted packet with a reception probability that depends on the nodes respective locations. Note further that in all broadcast wireless networks, the role of the multiple access or MAC protocol is fundamental to managing interference. In our work, we assume orthogonal access, such as *random TDMA*, thereby obviating the need to model multi-access interference. Such a set-up is admittedly limited but nonetheless useful, as it encompasses practical network scenarios such as a single-cell CSMA/CA [5], [6].

Finally, we emphasize that we only focus on the dissemination latency (i.e., the time needed for all nodes to communicate and receive the entire file) and do *not* consider the latency caused by encoding/decoding which has been studied separately in the literature [7]. In fact, [8], [9] explores design of a sparse network coding matrix that decreases encoding/decoding time significantly. Clearly, the net latency of data dissemination is the sum of our result and the encoding/decoding time.

The rest of the paper is organized as follows: Section II summarizes related works in data dissemination. Then, Section III describes the system model and basic assumptions used in this paper. The gossip-based data dissemination using network coding in wireless networks is introduced in Section IV. In Section V, we derive an upper bound on dissemination latency. Performance evaluations are presented in Section VI and the paper concludes with suggestions for future work in Section VII.

Notations: Bold capitals (e.g. $\mathbf{A}$) represent matrices and bold lowercase symbols (e.g. $\mathbf{m}$) denote vectors. The i-th entry of a vector $\mathbf{m}$ is denoted by m_i and superscript ^{T} denotes matrix transpose. The number of i-combinations from a given set of N elements, when order doesn't matter, is denoted by $C(N, i)$. The cardinality of a set S is defined as number of elements S has and it is denoted by $|S|$. The equality between two subspaces S_1 and S_2 is denoted by $S_1 \equiv S_2$.

II. RELATED WORKS

A. Data Dissemination in Wireless Networks

Data dissemination initially among wired clients first emerged as an appealing alternative to the traditional client-server model [10]. Due to the exponential growth of wireless networks, there has been considerable interest in the sharing problem between wireless nodes (such as cellular phones or PDAs) that are interconnected *wirelessly*. Clearly, data dissemination in wireless networks differs from the wired scenario in significant ways - the broadcast nature of wireless contributes (potentially) to multi-access interference. As a result, simultaneous reception of multiple packets in a wireless network is typically limited. Furthermore, wireless links are half-duplex due to hardware constraints; i.e., a node may not simultaneously transmit and receive due to the lack of sufficient isolation between the two paths.

Despite these differences, gossip-based protocols - originally applied for dissemination over wired networks - have remained as the algorithmic family of choice in wireless networks for dissemination, as they inherit the desired balance between simplicity and robustness [11]. Some modifications have been applied to make these protocols consistent with wireless properties. For instance, when a node transmits a packet in a wireless network, every node within its transmission range receives the packet [12], [13] in contrast to to gossip algorithms in wired networks that are based on unicast communication with a randomly chosen neighbor. However, the main feature of gossip-based algorithms is preserved - every node in the network acts simply based on its *local* state information.

B. Network Coding for Dissemination

A relatively new approach to decentralized data dissemination is based on network coding, first introduced for multicasting in wired networks [14], [15], [16], [17], [18]. Authors in [19] exploit random (linear) network coding within a gossip-based dissemination protocol for wired networks and show that, in a fully connected network, network coding can improve dissemination latency at the cost of a small overhead associated with each packet. In fact, they show that, in a network with N nodes, data can be diffused in $O(N)$ time using a coding-based gossip algorithm rather than $O(NlogN)$ without network coding. Mosk-Aoyama and Shah extend the result in [19] to a wired network with arbitrary topology [20] and show how the graph topology affects the performance of the coding-based dissemination algorithm.

For wireless networks, network coding was first exploited for wireless broadcasting - treated as a one-to-many data-dissemination problem - using simple XORs [21] that demonstrated bandwidth efficiency over traditional wireless broadcast approaches. Recently, [22] used network coding within a gossip-based algorithm (rumor-spreading) to diffuse information in an ad-hoc wireless network. This was continued by [23] who studied performance of such dissemination due to real-world MAC schemes.

There is a plausibility argument as to why network coding provides substantial benefits for data dissemination. As mentioned before, gossip algorithms impose restrictions on the information possessed by a node; i.e., every node has only a local view of the system state at any time. This is analogous to the initial state in our scenario, where each node has only a (small) unique part of the full file, and seeks to gather the other pieces. With time, a node gathers some of the other pieces but does not have any information about what pieces the neighboring nodes may possess. It is natural that, at any time, different nodes in the network will have acquired (at least some) non-overlapping pieces. Intuitively, this suggests that if each node encodes all the data it presently contains (via network coding) and broadcasts it, recipient nodes will have acquired coded versions about the missing pieces. In time, each node will be able to decode the full file, after a sufficient number of such encoded packet transmissions from other nodes, as subsequently described.

III. SYSTEM MODEL

As usual, a network graph is denoted as $G(V,E)$, with $|V|=N$ nodes and links $E\subset V\times V$. We assume that the network is slotted (i.e., all nodes are synchronized) for simplicity and that all transmissions occur synchronously with a common clock. Further, without loss of generality, we assume that during each time slot, a node $v\in V$ can broadcast exactly one packet. When node v broadcasts, node $u\in V$ receives the signal correctly with probability P_{vu}. We consider an interference-free (orthogonal) access that allows only one node to transmit at a time. This includes, among others, a single-cell 802.11-type infrastructure network based on CSMA/CA if all nodes lie within the (common) carrier sensing range. The probability of a node capturing the common channel at any time is assumed to be uniform among all nodes. Finally, we only consider networks with fixed topology, i.e., where the topology and link capacities do not change over time.

IV. DATA DISSEMINATION USING NETWORK CODING: ARBITRARY NETWORK TOPOLOGY

Assume that each node u initially has a single *information packet* x_u to be shared with every other node in the network. Hence, the set of unique (information) packets in the network, initially and at all subsequent times, is given by $\{x_1,\dots,x_N\}$ for a network with N nodes. Each information packet is a vector of r symbols, where each symbol is an element of a finite field $\mathbb{F}_{2^q}$, i.e., $x_u\in\mathbb{F}_{2^q}^r$ for each node $u\in V$. For convenience, assume that q divides the length of packets transmitted (otherwise, zero padding is applied). Moreover, all packets are linearly independent vectors in $\mathbb{F}_{2^q}$, reflecting the fact that nodes have different information to share[1]. The results and derivations presented in this paper can be extended to a case when some nodes have more than one message and some have none or when all the messages are there with one particular node to start with.

With time, each node receives a sequence of linear combinations of information packets at the other nodes. Hence, after a sequence of broadcasts, node $u\in V$ possesses a set of coded messages, $S_u(t)$ at time (slot) t.

$$S_u(t)=\{m_1,m_2,...,m_{|S_u(t)|}\},\tag{1}$$

---

[1] For more information about linear independence in finite fields, refer to [24], [25].

Each message m_i is a linear combination of the underlying *information packets*[2], initially possessed by the nodes and can be represented as

$$m_i = \sum_{k=1}^{N} \alpha_{i,k} x_k = \boldsymbol{\alpha}_i^T \mathbf{x}, \quad i = 1, 2, ..., |S_u(t)|, \tag{2}$$

where some of the coefficients $\alpha_{i,k}$ may be zero (if the corresponding information packet is not present at the transmitting node at that time). For each message m_i, $\alpha_{i,k}$s are called its *network coding coefficients*, and they are available through the header of the packet containing m_i. As discussed in [26], in a network coding system, each packet consists of two parts: a header that contains the network coding coefficients and a body that carries the encoded message. This header is a price to pay to use the network coding. However, if the size of the information packets (and hence the size of the messages) is reasonably large, this overhead is negligible. That being said, for each message m_i at node u, network coding coefficients are available.

Clearly, $S_u(t)$ (set of messages at node u at time t) spans a subspace in $\mathbb{F}_{2^q}^r$, as observed by rewriting Eq. (2) in the following form:

$$\mathbf{m}_u(t) = \mathbf{A}_u(t)\, \mathbf{x}, \tag{3}$$

where $\mathbf{A}_u$ is the coefficient matrix consisting of NC coefficients and $\mathbf{x}$ is the N-vector of all the information packets in the network, given by

$$\begin{aligned} \mathbf{x} &= [x_1 \;\; x_2 \;\; \ldots \;\; x_N]^T, \\ \mathbf{m}_u(t) &= [m_1 \;\; m_2 \;\; \ldots \;\; m_{|S_u(t)|}]^T, \\ \mathbf{A}_u(t) &= \begin{bmatrix} \alpha_{1,1} & \alpha_{1,2} & \cdots & \alpha_{1,N} \\ \vdots & \vdots & \ddots & \vdots \\ \alpha_{|S_u(t)|,1} & \alpha_{|S_u(t)|,2} & \cdots & \alpha_{|S_u(t)|,N} \end{bmatrix}. \end{aligned} \tag{4}$$

is defined by $\alpha_{i,j}$, the j-th coefficient used in the i-th message m_i received by node u.

From the received broadcast messages, a node can decode all the information packets at time t if the rank of its coefficient matrix, $\mathbf{A}_u(t)$, equals N, the total number of unique information packets in the network. In the next section, we use this observation to put an upper bound on dissemination latency in the network.

---

[2] Recall that each node u starts with a single information packet x_u to share with the rest of the network.

If node u captures the channel at any time slot t, it transmits a linear combination of all the messages that it currently contains, as follows:

$$y_u(t) = \sum_{i=1}^{|S_u(t)|} \beta_i m_i, \tag{5}$$

where $y_u(t)$ denotes a transmitted packet at time t, $S_u(t)$ is a set of messages node u contains at time t, and $\beta_i, \;\; i = 1, 2, ..., |S_u(t)|$, are random finite numbers selected from $\mathbb{F}_{2^q}$. Using (3), the transmitted message by node u at time t can be written in terms of *information packets* as follows:

$$\begin{aligned} y_u(t) &= \boldsymbol{\beta}\mathbf{m}_u(t-1) \\ &= \boldsymbol{\beta}\mathbf{A}_u(t-1)\mathbf{x} \\ &= \boldsymbol{\alpha}'\mathbf{x}, \end{aligned} \tag{6}$$

where $\boldsymbol{\alpha}' = \boldsymbol{\beta}\mathbf{A}_u(t-1)$ presents network coding coefficients of information packets used by node u to transmit a message at time t. As mentioned before, these coefficient are send a long with $y_u(t)$.

V. STOPPING TIME

The data dissemination algorithm terminates when *all* nodes are able to decode the broadcast messages to recover the underlying N set of information packets, which happens when Eq. (3) for all $u \in V$ has a unique solution, i.e., when the coefficient matrix at each node has full rank N. Hence, the stopping time $\mathcal{T}$ is defined as the first time when the full rank condition is achieved:

$$\mathcal{T} = \min_t \{rank(\mathbf{A}_u(t)) = N \; \forall u \in V\}. \tag{7}$$

Because matrix $\mathbf{A}_u$ has rank N if and only if $S_u(t)$, the subspace scanned by messages in u at time t, has dimension N. The stopping time can also be defined as follows:

$$\mathcal{T} = \min_t \{dim(S_u(t)) = N \; \forall u \in V\}. \tag{8}$$

Clearly, $\mathcal{T}$ is an integer random variable over $[N, \infty)$[3]. We next seek the expected value $\mathbb{E}[\mathcal{T}]$ as a performance metric for algorithm design. In general, $\mathbb{E}[\mathcal{T}]$ is difficult to compute; hence, we resort to bounds.

---

[3] To diffuse N packets, we need at least N transmissions, which in wireless networks require at least N time slots.

A. upper bound for Mean Stopping Time

As mentioned above, $S_u(t)$ is the set of packets that node u possesses at time t. Each packet is an r vector in a finite field $\mathbb{F}_{2^q}$ (i.e., it belongs to $\mathbb{F}_{2^q}^r$). Moreover, we assume that packets in $S_u(t)$ are independent. Hence, the cardinality of $S_u(t)$ is the same as its dimension.

By our formulation, every node initially starts with an information packet. In other words, at $t = 0$, there is one and only one (independent) packet in $S_u(0)$, i.e., $dim(S_u(0)) = 1 \ \forall u \in V$. With time, the information spreads to all nodes upon sharing via broadcast, resulting in a final per node dimension of N at the time of stopping. Hence, each node dimension is raised by $N-1$ during the information dissemination, and the overall dimension increase among all the nodes is $N(N-1)$. Let us define $D(t)$ as the total dimension increase (among all the nodes) at time t. Obviously, $D(t)$ can be written as follows:

$$D(t) = \sum_{u \in V} dim(S_u(t)) - N. \tag{9}$$

Clearly, the information has spread to all nodes when $D(t) = N(N-1)$. Now, let $\mathcal{T}_i$ denote the number of time slots until the total dimension increases by $i(N-1)$. It can be written as follows:

$$\mathcal{T}_i = \min_t \{D(t) \geq i(N-1)\}. \tag{10}$$

By definition $\mathcal{T}_0 = 0$ and the information spreads to all the nodes at $\mathcal{T}_N$, i.e., $\mathcal{T} = \mathcal{T}_N$.

The following lemma gives an upper bound for the probability of the message sets at two nodes spanning the same subspace when $t = \mathcal{T}_i$.

Lemma 1. *At $t = \mathcal{T}_i$, the probability that any two nodes (e.g., u, v) have the same subspace can be bounded from above as follows*[4]*:*

$$P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)) \leq \sum_{k=1}^{N-1} \min\left(\frac{N-i}{N-k-1}, \frac{i}{k}\right) P(dim(S_v(t)) = k+1). \tag{11}$$

Proof: See appendix.

---

[4] Note that in Eq. 25 (and in similar cases henceforth), $S_u(t) \equiv S_v(t)$ indicates the equality between two subspaces, the one spanned by elements in S_u and the one spanned by elements in S_v.

Intuitively, the probability that two nodes have the same subspace at $\mathcal{T}_i$ is calculated using the law of total probability: probability that one of them has dimension k multiplied by the probability that the other one has the same subspace. The latter can be calculated by recalling that $\mathcal{T}_i$ represents the number of time slots at which the total dimension increase is $i(N-1)$. We next explore the dimension of node $u \in V$ at time $\mathcal{T}_i$. The following lemma gives an upper bound on the probability of node u having dimension k at $\mathcal{T}_i$.

Lemma 2. *The probability that node u has dimension k at time $\mathcal{T}_i$ is given by:*

$$\begin{aligned} & P(dim(S_u(\mathcal{T}_i)) = k) = \\ & \frac{\sum_{j=0}(-1)^j C(N-1,j)C(i(N-1)+N-2-jN-k,N-2)}{\sum_{j=0}(-1)^j C(N,j)C(i(N-1)+N-1-jN,N-1)}. \end{aligned} \tag{12}$$

Proof: See appendix.

By definition, at time $\mathcal{T}_i$, the dimension has increased by $i(N-1)$ and this comes from N nodes. Now the probability that one node has dimension increase k is in fact the traditional ball and bins problem.

The following theorem provides an upper bound on expected number of time slots between $\mathcal{T}_i$ and $\mathcal{T}_{i+1}$.

Theorem 1. *For $0 \le i \le N-2$:*

$$\mathbb{E}[\mathcal{T}_{i+1} - \mathcal{T}_i] \le \frac{N-1}{\frac{1}{2N}(\sum_{u,v\in V} P_{uv})(1 - P(S_u(\mathcal{T}_{i+1}) \equiv S_v(\mathcal{T}_{i+1})))}, \tag{13}$$

and for $i = N-1$

$$\mathbb{E}[\mathcal{T}_N - \mathcal{T}_{N-1}] \le \frac{N(N-1)}{\frac{1}{2N}(\sum_{u,v\in V} P_{uv})}. \tag{14}$$

Proof: See appendix.

Finally, the following theorem, which is the main contribution of this paper, gives an upper bound on the stopping time $\mathcal{T}$.

Theorem 2. *Let $\mathcal{T}$ be stopping time. Then*

$$\begin{aligned} \mathbb{E}[\mathcal{T}] &= \mathbb{E}[\mathcal{T}_N] \\ &\le \frac{N-1}{\frac{1}{2N}\sum_{u,v\in V} P_{uv}} \left(\sum_{i=1}^{N-1} \frac{1}{1 - P\big(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)\big)} + N \right). \end{aligned} \tag{15}$$

Proof: See appendix.

Note that to numerically calculate the upper bound given in Eq. 15, we need to combine the results in Eqs. 25 and 12. Since each node is initialized with a single packet, it needs to acquire the remaining $N-1$ packets from other nodes for the process to terminate. Hence a total of $N(N-1)$ successful packet transmissions must occur. Due to the broadcast nature of wireless, multiple receive nodes hear each transmission and may decode the transmitted packet (according to their reception probability; higher reception probability results in a higher chance of decoding). Therefore, the number of time slots required is inversely proportional to reception probability as captured by the first part of the upper bound. The second part of the upper bound represents the fact that a successfully received packet v at a node is only useful if it does not belong to the subspace spanned by existing packets; i.e., it is ‘innovative’. Again intuitively, the probability of a packet being innovative at a node decreases with time, as the subspace spanned by existing packets is always monotonic non-decreasing.

In an interference-free network where only one node transmits in each time slot, Theorem 2 gives an upper bound on dissemination latency when NC is used. As expected, the upper bound depends on reception probabilities and the number of nodes inside the network. In the following two lemmas, we consider two extreme cases, a fully connected wireless network and a sparsely connected network. These two cases illustrate how reception probability affects dissemination based on NC in a wireless network. We show that no matter what the reception probabilities are, the average stopping time is between $O(N)$ and $O(N^2)$ as long as the network stays connected.

A wireless network $G(V,E)$ is considered fully connected when for every two nodes $u, v \in V$, $P_{uv} > 0$. In other words, in a fully connected network, every node is within the transmission range of all the others.

Lemma 3. *In a fully connected wireless network in which every node can receive a packet from any other node in the network with a nonzero probability, the average stopping time is of order* $O(N)$ *when network coding is applied.*

proof: Appendix.

Above, the corollary is consistent with the result of the data dissemination in a wired network when network coding is adapted. The authors in [19] show that the stopping time increases linearly with the size of the wired network (i.e., it is of order $O(N)$) if the network is fully connected; i.e., each node is connected to every other node.

A wireless network $G(V, E)$ is sparsely connected when the network is connected and every node is in transmission range of at most two other nodes. An example of a sparsely connected wireless network is a linear network when each node can only communicate with its close neighbors.

Lemma 4. *In a sparsely connected wireless network, the average stopping time is of order* $O(N^2)$ *when network coding is applied.*

proof: Appendix.

Clearly, Lemma 3 gives the best achievable time [5] (smallest number of time slots), and Lemma 4 gives the worst time (largest number of time slots needed). In other words, the above two lemmas show that for data dissemination in a wireless network with N nodes, the average stopping time is between $O(N)$ and $O(N^2)$, independent of the underlying reception probability of the nodes.

VI. PERFORMANCE EVALUATION

In this section, we present results from a system simulation conducted using MATLAB R2008b that conforms to the data dissemination model described. The objective is to explore tightness of our stopping time upper bound, given in Eq. (15), for data dissemination in a wireless network with general topology and interference-free random access scheduler (i.e., only one node captures the channel and transmits, while all others listen). At the physical layer, we use QAM modulation with no channel coding. The results reported are based on simulations conducted for two simple and useful topologies: regular linear and 2-D grid. Such structured topologies help with better understanding of the model behavior as the number of nodes increase.

A. Reception Probability

We assume that all nodes use the same transmission power $\mathcal{P}$ and modulation scheme to broadcast packets. The wireless channel undergo Rayleigh envelope fading, and the path loss

---

[5] especially when p=1



(a)

(b)

Fig. 1. Example of a network with (a) linear topology (b) grid topology

exponent is η. Assume node u sends a packet to node v which is $d(u,v)$ far away. Let $s_{u,v}$ be the received power at v in the clear channel (i.e., no interference). Then $s_{u,v}$ follows an exponential random variable with mean $\mathcal{P} \cdot d(u,v)^{-\alpha}$ given by the following probability distribution function (pdf):

$$f(s_{u,v}) = \frac{1}{\mathcal{P}d(u,v)^{-\eta}} exp(-\frac{s}{\mathcal{P}d(u,v)^{-\eta}}). \tag{16}$$

Node v, the receiver, can decode successfully the packet transmitted by u if its received Signal-to-Noise (SINR) ratio exceeds a threshold[6]:

$$P_{u,v} = Pr(\frac{s_{u,v}}{\mathcal{N}_0} \geq z), \tag{17}$$

The $\mathcal{N}_0$ is the variance of additive white Gaussian noise, assumed to be 4×10^{-14} at all the receivers [7], and z is the capture reception threshold whose value depends on channel coding and modulation.

B. Linear Grid

Here, nodes are located in a line, with equal distance between neighbors. At first, we let the transmit power remain fixed and increase the size of the network by adding more nodes. Figure

---

[6] As mentioned before, we are assuming an interference free communication

[7] Noise Power is calculated for the bandwidth of 10MHz and in temperature 300K. This value, however, does not affect the result of the simulation.



Fig. 2. Both the analytical upper bound and the simulation result are increasing linearly at first, and after $N = 30$ they start increasing non-linearly versus the number of nodes in the network, $d = 30$, $\mathcal{P} = 20 \times 10^{-6}$, $\mathcal{N}_0 = 4 \times 10^{-14}$.

2 presents the simulation result and the analytical upper bound for the linear network. As one can see, the upper bound given in Eq. 15 closely follows the trend of the simulation results.

When there are only a few nodes in the network, stopping time has a linear relation with the number of nodes in the network. However, when the size of the network keeps increasing, the linear relation is not valid anymore. This is consistent with our findings in Lemmas 3 and 4. For a small number of nodes in the network, nodes are in transmission range of each other; i.e., a transmitted packet is heard by all of the nodes in the network (with nonzero probability $P_{uv} > 0$); hence, the stopping time is $O(N)$. On the other hand, when the size of the network keeps expanding, after a while we have $P_{uv} = 0$ for some nodes in the network and that affects the trend of the dissemination delay. In Figure 2, after $N = 30$, the stopping time (from both the simulation and analytical result) starts to increase nonlinearly. In fact, one can see that the stopping time is $O(N^2)$ after $N = 30$.

Finally, we change transmission power to see its effect on dissemination latency and the accuracy of the upper bound in Eq. (15). The result is presented in Figure 3. Clearly, decreasing transmission power reduces nodes' coverage and results in increased stopping time. However, the relation between the stopping time and the transmission power is very interesting and is sort of hidden in Eq. (15).

For a fixed network, we start with $0dB$ power and decrease it to $-40dB$. At first, nodes are in



Fig. 3. Analytical upper bound and simulation results versus nodes' transmission power for linear network, $\mathcal{N}_0 = 4 \times 10^{-14}$.

transmission range of each other. In that case, the relation between the transmission power and the stopping time is linear. However, after a point, nodes start falling out of the coverage range of each other. When that happens, stopping time starts increasing nonlinearly with transmission power. Although our formula in Eq. 5 does not show this relation directly (counter to the result with size of the network), it has the same trend as the simulation results.

C. 2-D Grid

In a 2-D grid topology, nodes are located on a equispaced 2-D lattice as depicted in Figure 1-b. As for the linear network, we first let the transmission power remain fixed while increasing the size of the network by adding more nodes. Figure 4 presents the simulation result and the analytical upper bound for the grid network with five different sizes.

In an $m \times n$ grid network with equispaced d, the distance between every two nodes is less than or equal to $d\sqrt{m^2 + n^2}$, which happens to be smaller than the transmission range of all the nodes in our simulation. In other words, for the fixed transmission power, each node can hear from all other nodes with nonzero probability. It is for this reason that the stopping time has a linear trend with the size of the network (Theorem 3).

Finally, for different transmission power, analytical upper bounds and simulation results are presented in Figure 5. As we argued for the network with linear topology, although the relation between the transmission power and the dissemination latency can not be directly inferred from



Fig. 4. Analytical and simulation results when size of network is changing and nodes' transmission power is fixed for grid network, $d = 30$, $\mathcal{P} = 20 \times 10^{-6}$, $\mathcal{N}_0 = 4 \times 10^{-14}$. Since nodes are in coverage range of each other dissemination latency increases linearly as we show in Theorem 3.



Fig. 5. Analytical upper bound follows the simulation results trend when nodes' transmission is changing power for grid network, $\mathcal{N}_0 = 4 \times 10^{-14}$.

the proposed upper bound in Eq. (15), it follows the simulation results by the same trend.

D. Advantage of Network Coding

In this subsection we compared the dissemination latency with network coding using computer simulation to a baseline *random* non-NC algorithm. The non-NC approach - termed random selection - operates as follows: whenever a node captures the channel it *randomly selects* an

TABLE I

STOPPING TIME FOR DISSEMINATION ALGORITHM IN A LINEAR NETWORK WITH AND WITHOUT NETWORK CODING. $d = 30$, $\mathcal{P} = 20 \times 10^{-6}$

# nodes	23	27	30	35
NC-based	84.46	100.94	121.54	157.59
random-selection	1189.6	2180.8	3148.9	3713.4

TABLE II

STOPPING TIME FOR DISSEMINATION ALGORITHM IN GRIP NETWORK WITH AND WITHOUT NETWORK CODING. WE HAVE $d = 30$, $\mathcal{P} = 20 \times 10^{-6}$

# nodes	4×4	4×5	5×5	6×4	6×6
NC-based	59.34	78.88	90.4	110.5	130.72
random-selection	684.3	1044.4	2275.8	2836.7	3724.4

information message from its buffer and broadcasts the selected packet. Table I compares the mean time needed to diffuse data in a linear network with network coding vs. the random selection algorithm. The performance of the random selection algorithm and NC-based algorithm for a 2-D grid topology is compared in Table II. As expected, network coding based dissemination outperforms the random selection algorithm by an order of magnitude. The reception probabilities are calculated as explain in Section V.

VII. CONCLUSION

In an all-to-all communication within a wireless network, we study the use of using network coding was studied in this paper. In a wireless network with general topology, we provide an analytical upper bound for the amount of time needed to spread information through the whole network. Our result show that by using network coding the stopping time is between $O(N)$ and $O(N^2)$ where N is number of nodes inside the network. Our simulation results indicates that our proposed upper bound follows the trend of the stopping time in networks with linear and grid topologies.

Our result here is limited to the following assumption, only one (random) node is transmitting in each time slot. In other words, we are assuming an interference-free scheduler. This assumption is valid for small networks in which nodes are in carrier sensing coverage of each other.

CSMA/CA-type MAC in such networks are pretty close to interference free thanks to collision avoidance protocol. However, this assumption no longer is valid in large networks. In fact, the ability of (multiple) simultaneous transmissions (called spatial reuse) is one of the advantages of wireless networks which is ignored in our result. Our future work focuses on extending our result here to networks with spatial reuse.

REFERENCES

[1] A. Kermarrec, L. Massoulié, and A. Ganesh, "Probabilistic reliable dissemination in large-scale systems," *IEEE Trans. Parallel and Distributed systems*, pp. 248–258, 2003.

[2] A. Demers, D. Greene, C. Hauser, W. Irish, J. Larson, S. Shenker, H. Sturgis, D. Swinehart, and D. Terry, "Epidemic algorithms for replicated database maintenance," in *Proceedings of the sixth annual ACM symposium on principles of distributed computing*, 1987, pp. 1–12.

[3] Y. Minsky, "Spreading rumors cheaply, quickly, and reliably," Ph.D. dissertation, 2002.

[4] W. Xiumin, W. Jianping, and X. Yinlong, "Data dissemination in wireless sensor networks with network coding," *EURASIP Journal on Wireless Communications and Networking*, 2010.

[5] T. Ho and K. Chen, "Performance analysis of ieee 802.11 csma/ca medium access control protocol," in *Proceedings of Seventh IEEE International Symposium on Personal, Indoor and Mobile Radio Communications*, vol. 2, 1996, pp. 407–411.

[6] G. Bianchi, L. Fratta, and M. Oliveri, "Performance evaluation and enhancement of the csma/ca mac protocol for 802.11 wireless lans," in *Proceedings of Seventh IEEE International Symposium on Personal, Indoor and Mobile Radio Communications*, vol. 2, 1996, pp. 392–396.

[7] M. Wang and B. Li, "How practical is network coding?" in *Proceedings of 14th IEEE International Workshop on Quality of Service*, 2006, pp. 274–278.

[8] D. Vukobratović, Č. Stefanović, and V. Crnojević, "On low-complexity network coding for data collection in wireless sensor networks," 2008.

[9] X. Li, W. Mow, and F. Tsang, "Rank distribution analysis for sparse random linear network coding," in *Proceedings of International Symposium on Network Coding (NetCod)*, 2011, pp. 1–6.

[10] P. Eugster, R. Guerraoui, A. Kermarrec, and L. Massoulié, "Epidemic information dissemination in distributed systems," *Computer*, vol. 37, no. 5, pp. 60–67, 2005.

[11] T. Aysal, M. Yildiz, A. Sarwate, and A. Scaglione, "Broadcast gossip algorithms for consensus," *IEEE Trans. Signal Processing*, vol. 57, no. 7, pp. 2748–2761, 2009.

[12] R. Prakash, A. Schiper, M. Mohsin, D. Cavin, and Y. Sasson, "A lower bound for broadcasting in mobile ad hoc networks," *Tech. Rep. IC/2004/37 École Polytechnique Fédérale de Lausanne, Switzerland*, June.

[13] S. El Rouayheb, M. Chaudhry, and A. Sprintson, "On the minimum number of transmissions in single-hop wireless coding networks," in *Proceedings of IEEE Information Theory Workshop*, 2007, pp. 120–125.

[14] R. Ahlswede, N. Cai, S. Li, and R. Yeung, "Network information flow," *IEEE Trans. Information Theory*, vol. 46, no. 4, pp. 1204–1216, 2000.

[15] S. Li, R. Yeung, and N. Cai, "Linear network coding," *IEEE Trans. Information Theory*, vol. 49, no. 2, pp. 371–381, 2003.

[16] T. Ho, M. Medard, J. Shi, M. Effros, and D. Karger, "On randomized network coding," in *Proceedings of Annual allerton Conf. Communication control and computing*, vol. 41, no. 1, 2003, pp. 11–20.

[17] T. Ho, M. Medard, R. Koetter, D. Karger, M. Effros, J. Shi, and B. Leong, “A random linear network coding approach to multicast,” *IEEE Trans. Information Theory*, vol. 52, no. 10, pp. 4413–4430, 2006.

[18] R. Koetter and M. Medard, “An algebraic approach to network coding,” *IEEE/ACM trans. Networking*, vol. 11, no. 5, pp. 782–795, 2003.

[19] S. Deb, M. Médard, and C. Choute, “Algebraic gossip: A network coding approach to optimal multiple rumor mongering,” *IEEE Trans. Information Theory*, vol. 52, no. 6, pp. 2486–2507, 2006.

[20] D. Mosk-Aoyama and D. Shah, “Information dissemination via network coding,” in *IEEE Intl. Symposium on information theory*, 2006, pp. 1748–1752.

[21] D. Nguyen, T. Tran, T. Nguyen, and B. Bose, “Wireless broadcast using network coding,” *IEEE Trans. Vehicular Technology*, vol. 58, no. 2, pp. 914–925, 2009.

[22] C. Fragouli, J. Widmer, and J. Le Boudec, “Efficient broadcasting using network coding,” *IEEE/ACM Trans. Networking*, vol. 16, no. 2, pp. 450–463, 2008.

[23] A. Asterjadhi, E. Fasolo, M. Rossi, J. Widmer, and M. Zorzi, “Toward network coding-based protocols for data broadcasting in wireless ad hoc networks,” *IEEE Trans. Wireless Communications*, vol. 9, no. 2, pp. 662–673, 2010.

[24] E. Horowitz, “Modular arithmetic and finite field theory: A tutorial,” in *Proceedings of the second ACM symposium on Symbolic and algebraic manipulation*, 1971, pp. 188–194.

[25] R. McEliece, *Finite fields for computer scientists and engineers*. Springer, 1987.

[26] P. Chou, Y. Wu, and K. Jain, “Practical network coding.”

APPENDIX A

PROOF OF THEOREMS

Lemma 1: At $t = \mathcal{T}_i$, the probability that any two nodes (e.g. u, v) have the same subspace can be bounded from above as follows:

$$P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)) \leq \sum_{k=1}^{N-1} \min(\frac{i}{k}, \frac{N-i}{N-k-1}) P(dim(S_v(t)) = k+1).$$

Proof: For the sake of simplicity, we will write $S_u(\mathcal{T}_i)$ and $S_v(\mathcal{T}_i)$ as S_u and S_v respectively. By using law of total probability we have:

$$P(S_u \equiv S_v) = \sum_{k=1}^{N-1} P(S_u \equiv S_v | dim(S_v) = k+1) P(dim(S_v) = k+1). \tag{18}$$

The reason that in the summation k starts from one instead of zero is that $P(S_u = S_v | dim(S_v) = 1) = 0$. That is because we assume nodes initially contain different information packets. To calculate $P(S_u = S_v | dim(S_v) = k+1)$, let define E_v as the set of all nodes (including v itself) which spans the same space as S_v:

$$E_v = \{u | S_v \equiv S_u\}. \tag{19}$$

Since we know $dim(S_v) = k+1$, each member of E_v has dimension $k+1$, which means we have total dimension *increase* of at least $|E_v|k$. At time $t = \mathcal{T}_i$, dimension of whole system is at most by $i(N-1)$ by definition of $\mathcal{T}_i$ in Eq. (10). Therefore the following inequality holds:

$$|E_v|k \leq i(N-1), \tag{20}$$

which implies

$$|E_v| \leq i(N-1)/k. \tag{21}$$

On the other hand, at time $t = \mathcal{T}_i$, nodes need to capture $N(N-1) - i(N-1) = (N-i)(N-1)$ dimension to stop. Node is set E_v, each need $N-k-1$ dimension increase. So the total amount of dimension increase nodes in E_v require is $|E_v|(N-k-1)$ which cannot be greater than total amount of needed dimention at time $\mathcal{T}_i$. Hence the following inequality holds:

$$|E_v| \leq \frac{(N-i)(N-1)}{(N-k-1)} \tag{22}$$

Since $|E_v|$ satisfies both inequalities in Eq. (21) and Eq. (21), it satisfies the following:

$$|E_v| \leq (N-1)\min\left(\frac{N-i}{N-k-1}, \frac{i}{k}\right). \tag{23}$$

Now we can calculate $P(S_u \equiv S_v | dim(S_v) = k+1)$. We know that $|E_v|$ nodes have the same dimension as node v. Hence a randomly selected node u (from $N-1$ posibilities) has the same dimension of node v with probability $\frac{|E_v|}{N-1}$. Therefore,

$$P(S_u \equiv S_v | dim(S_v) = k+1) \leq \min\left(\frac{N-i}{N-k-1}, \frac{i}{k}\right). \tag{24}$$

By substituting these results in Eq. (25), we have the following inequality:

$$P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)) \leq \sum_{k=1}^{N-1} \min\left(\frac{N-i}{N-k-1}, \frac{i}{k}\right) P(dim(S_v) = k+1). \tag{25}$$

■

Lemma 2: Probability that node u has dimension k at time $\mathcal{T}_i$ is given by:

$$P(dim(S_u(\mathcal{T}_i)) = k) = \\ \frac{\sum_{j=0}(-1)^j C(N-1, j) C(i(N-1) + N - 2 - jN - k, N-2)}{\sum_{j=0}(-1)^j C(N, j) C(i(N-1) + N - 1 - jN, N-1)}.$$

Proof: The probability of node u having dimension $k+1$ at $\mathcal{T}_i$ is equivalent to the probability of a dimension increase of k for node u at $\mathcal{T}_i$. At time $\mathcal{T}_i$, by definition, the overall dimension increase among all nodes is $i(N-1)$. So, the problem is from the $i(N-1)$ increased dimension, which is the probability that k goes to node u given that the dimension increase of each node cannot be greater than $N-1$. This is a traditional ball and bins problem.

All possible outcomes of the ball and bins problem must have the same probability of occurrence. Here, all possible outcomes have the same probability because of the following assumptions:

- Nodes are equally lucky in capturing the channels and transmitting in each time slot.
- $P_{uv} = P_{vu}$
- In the initial state (beginning of dissemination), every node has one and only one information packet.

■

Theorem 1: For $0 \leq i \leq N-2$*:*

$$\mathbb{E}[\mathcal{T}_{i+1} - \mathcal{T}_i] \leq \frac{N-1}{\frac{1}{2N}(\sum_{u,v\in V} P_{uv})(1 - P(S_u(\mathcal{T}_{i+1}) \equiv S_v(\mathcal{T}_{i+1})))},$$

and for $i = N-1$

$$\mathbb{E}[\mathcal{T}_N - \mathcal{T}_{N-1}] \leq \frac{N(N-1)}{\frac{1}{2N}(\sum_{u,v\in V} P_{uv})}.$$

Proof: Suppose we are in time slot t where $t \in [\mathcal{T}_i, \mathcal{T}_{i+1})$. By definition, $D(t)$ presents a dimension increase at time t. At time slot t, node u would capture the channel and start transmitting with probability $1/N$. By our assumption, each node transmits one unit of information at each time slot; thus, when node u transmits, the dimension of node v would increase by 1 if it receives the packet transmitted by u (with probability P_{uv}) and if the packet contains at least one dimension that is not in v. This can be written as follows:

$$\mathbb{E}[D(t+1)-D(t)] = \sum_u \frac{1}{N} \sum_{v\neq u} P_{uv} P(\text{packet contains at least one dimension which is not in } v). \tag{26}$$

The second probability in above equation can be calculated using the following two events:

1) Set S_u should not fall into set S_v or mathematically speaking $S_u(t) \nsubseteq S_v(t)$.
2) Given above, the NC coefficients must be selected in such a way to cover some dimensions from $S_u(t)$ which are not in $S_v(t)$.

The second event above is calculated in [19] to be:

$$1 - (\frac{1}{q})^{|(S_u(t) \cap S'_v(t))|}, \text{ given } S_u(t) \nsubseteq S_v(t), \tag{27}$$

where $S'_v(t)$ is complement of $S_v(t)$ and the finite field is $\mathbb{F}_{2^q}$. Hence given u is transmitting a packet, we have:

$$\begin{aligned} &P(\text{packet contains at least one dimension which is not in } v) \\ &= P(S_u(t) \nsubseteq S_v(t))(1 - (\frac{1}{q})^{|(S_u(t) \cap S'_v(t))|}). \end{aligned} \tag{28}$$

Thus the average dimension increasing can be calculated as follows:

$$\mathbb{E}[D(t+1) - D(t)] = \sum_u \frac{1}{N} \sum_{v \neq u} P_{uv} P(S_u(t) \nsubseteq S_v(t))(1 - (\frac{1}{q})^{|(S_u(t) \cap S'_v(t))|}), \tag{29}$$

We assume $\frac{1}{q} \approx 0$ which is practical assumption. For example if we assign only 8 bits to NC, $\frac{1}{q} = \frac{1}{256} = .004$. In that case we can rewrite above equation as:

$$\mathbb{E}[D(t+1) - D(t)] = \sum_u \frac{1}{N} \sum_{v \neq u} P_{uv} P(S_u(t) \not\equiv S_v(t)). \tag{30}$$

In above summation, for any two nodes $u, v \in V$, we have a summation term $P(S_u(t) \nsubseteq S_v(t)) + P(S_v(t) \nsubseteq S_u(t))$. Clearly, $\{S_u(t) \not\equiv S_v(t)\} \subset \{S_u(t) \nsubseteq S_v(t)\} \cup \{S_v(t) \nsubseteq S_t(t)\}$ which results in the following inequalities:

$$P(S_u(t) \nsubseteq S_v(t)) + P(S_v(t) \nsubseteq S_u(t)) \geq P(S_v(t) \not\equiv S_u(t)) = 1 - P(S_v(t) \equiv S_u(t)) \forall u, v \in V. \tag{31}$$

Thus Eq. (30) can be rewritten as follows:

$$\begin{aligned}
\mathbb{E}[D(t+1)-D(t)] &= \sum_u \frac{1}{N} \sum_{v\neq u} P_{uv} P(S_u(t) \nsubseteq S_v(t)) && (32)\\
&\geq \frac{1}{N} \sum_u \sum_{v, v>u} P_{uv}(1-P(S_u(t) \equiv S_v(t)))\\
&\overset{(1)}{=} \frac{1}{2N}\Bigg(\sum_u \sum_{v, v>u} P_{uv}(1-P(S_u(t) \equiv S_v(t)))\\
&\qquad + \sum_v \sum_{u, u>v} P_{vu}(1-P(S_v(t) \equiv S_u(t)))\Bigg)\\
&= \frac{1}{2N} \sum_{u,v} P_{uv}(1-P(S_v(t) \equiv S_u(t))),
\end{aligned}$$

where equality (1) is drived by renaming the sum indexes and the last equality is the result of having $P_{uv} = P_{vu}$ and $P(S_v(t) \equiv S_u(t)) = P(S_u(t) \equiv S_v(t))$.

We know that by definition $D(\mathcal{T}_i) = i(N-1)$ so we can add up above statement for $t \in [\mathcal{T}_i, \mathcal{T}_{i+1})$:

$$\sum_{t\in[\mathcal{T}_i,\mathcal{T}_{i+1})} \mathbb{E}[D(t+1)-D(t)] = \frac{1}{2N}(\sum_{u,v\in V} P_{uv}) \sum_{t\in[\mathcal{T}_i,\mathcal{T}_{i+1})} (1-P(S_u(t) \equiv S_v(t))). \qquad (33)$$

In above derivation we also used this fact that $P(S_u(t) = S_v(t))$ does not depend on u and v as given by Lemma 1 and Lemma 2.

By definition of $\mathcal{T}_i$ and $D(t)$ we have:

$$\sum_{t\in[\mathcal{T}_i,\mathcal{T}_{i+1})} \mathbb{E}[D(t+1)-D(t)] = N-1. \qquad (34)$$

Now we consider two possibilities for i.

1) if $0 \leq i \leq N-2$ then Obviously we have:

$$P(S_u(\mathcal{T}_{i+1}) \equiv S_v(\mathcal{T}_{i+1})) \geq P(S_u(t) \equiv S_v(t)) \forall t \in [\mathcal{T}_i, \mathcal{T}_{i+1}). \qquad (35)$$

By above inequality and equalities Eq. (33) and (34) we have:

$$\begin{aligned}
N-1 &= \frac{1}{2N}(\sum_{u,v\in V} P_{uv}) \sum_{t\in[\mathcal{T}_i,\mathcal{T}_{i+1})} (1-P(S_u(t) \equiv S_v(t))) && (36)\\
&\geq \frac{1}{2N}(\sum_{u,v\in V} P_{uv}) \sum_{t\in[\mathcal{T}_i,\mathcal{T}_{i+1})} (1-P(S_u(\mathcal{T}_{i+1}) \equiv S_v(\mathcal{T}_{i+1})))\\
&= \frac{1}{2N}(\sum_{u,v\in V} P_{uv})(1-P(S_u(\mathcal{T}_{i+1}) \equiv S_v(\mathcal{T}_{i+1})))(\mathbb{E}[\mathcal{T}_{i+1}-\mathcal{T}_i]).
\end{aligned}$$

and by rearranging the terms we get:

$$\mathbb{E}[\mathcal{T}_{i+1} - \mathcal{T}_i] \leq \frac{N-1}{\frac{1}{2N}(\sum_{u,v \in V} P_{uv})(1 - P(S_u(\mathcal{T}_{i+1}) \equiv S_v(\mathcal{T}_{i+1})))}, \; i = 0, ..., N-2. \tag{37}$$

2) if $i = N-1$, then by definition, for all $u, v \in V \;\; S_u(\mathcal{T}_N) \equiv S_v(\mathcal{T}_N)$ which doesn't help us to obtain a bound on $\mathbb{E}[\mathcal{T}_{i+1} - \mathcal{T}_i] = \mathbb{E}[\mathcal{T}_N - \mathcal{T}_{N-1}]$. For that let consider a time slot before $\mathcal{T}_N$; i.e., $t = \mathcal{T}_N - 1$. In that time slot the following two statements are valid

- At least one of the nodes does not have the whole space; i.e. $\exists u \in V s.t. |S_u(t)| < N$
- At least one of the nodes does have the whole space; i.e. $\exists v \in V s.t. |S_v(t)| = N$

From the above statements we can conclude:

$$P(S_u(t) \equiv S_v(t)) \leq \frac{N-1}{N} \text{ for } t \in [\mathcal{T}_{N-1}, \mathcal{T}_N). \tag{38}$$

By substituting above equation in (30) and following the same argument as we did for the first case we will have:

$$\mathbb{E}[\mathcal{T}_N - \mathcal{T}_{N-1}] \leq \frac{N(N-1)}{\frac{1}{2N}(\sum_{u,v \in V} P_{uv})}. \tag{39}$$

■

Theorem 2: Let $\mathcal{T}$ be stopping time. Then

$$\begin{aligned} \mathbb{E}[\mathcal{T}] &= \mathbb{E}[\mathcal{T}_N] \\ &\leq \frac{N-1}{\frac{1}{2N}\sum_{u,v \in V} P_{uv}} \left(\sum_{i=1}^{N-1} \frac{1}{1 - P\big(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)\big)} + N \right). \end{aligned}$$

Proof:

$$\begin{aligned} \mathbb{E}[\mathcal{T}] &= \mathbb{E}[\mathcal{T}_N] \\ &= \sum_{i=1}^{N} (\mathbb{E}[\mathcal{T}_i - \mathcal{T}_{i-1}]) \\ &= \sum_{i=1}^{N-1} (\mathbb{E}[\mathcal{T}_i - \mathcal{T}_{i-1}]) + \mathbb{E}[\mathcal{T}_N - \mathcal{T}_{N-1}] \\ &\leq \frac{N-1}{\frac{1}{2N}\sum_{u,v \in V} P_{uv}} \left(\sum_{i=1}^{N-1} \frac{1}{(1 - P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)))} + N \right). \end{aligned} \tag{40}$$

■

Corollary 3: In a fully connected wireless network in which every node can receive packet from any other node in the network with a non-zero probability, the average stoping time is of order $O(N)$ when network coding is applied.

Proof: First let prove the following lemma:

Lemma 5. *There exist a finite number β such that the following is held:*

$$\sum_{i=1}^{N-1} \frac{1}{(1 - P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)))} \leq N\beta \tag{41}$$

Proof: By definition of the stopping time $\mathcal{T}$, $P(S_u(t) \equiv S_v(t)) < 1$ for $t < \mathcal{T}$. Let α be the largest number less than 1 such that $P(S_u(t) \equiv S_v(t)) \leq \alpha < 1$. Then

$$\sum_{i=1}^{N-1} \frac{1}{(1 - P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)))} \leq \frac{1}{1-\alpha} \sum_{i=1}^{N-1} 1 = \frac{N-1}{1-\alpha}. \tag{42}$$

□

We are assuming that nodes can receive packets from each other with probability at leat p. In other words, each node is in transmission rage of all other nodes and p is the smallest reception probability between every two nodes. Note that for $p = 1$, the wireless network acts like a wired network with a complete graph. Mathematically speaking:

$$P_{uv} \geq p \ \forall u, v \in V. \tag{43}$$

Using the above equation we have:

$$\sum_{u,v \in V} P_{uv} \geq N^2 \cdot \sum_{u,v \in V} p = N^2 \cdot p \tag{44}$$

Using the above equation and Lemma 5, Eq. 15 can be bounded as:

$$\begin{aligned} \mathbb{E}[\mathcal{T}] &\leq \frac{N-1}{\frac{1}{2N}\sum_{u,v \in V} P_{uv}} \left(\sum_{i=1}^{N-1} \frac{1}{(1 - P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)))} + N \right) \\ &\leq \frac{N-1}{\frac{Np}{2}} (N\beta + N) = \frac{2}{p}(N-1)(1+\beta). \end{aligned} \tag{45}$$

Therefore, in this case time is of order $O(N)$.

Corollary 4: In a sparsely connected wireless network the average stoping time is of order $O(N^2)$ *when network coding is applied.*

In this case each node only receives packets from at most two other nodes. Let assume $p > 0$ be the smallest reception probabilities for all the nodes inside the network. Note that p can not be zero because we are assuming the network is connected which means every node receives data with non-zero probability from at leat one of its neighbors. In other words:

$$\forall u \in V \ \ \exists v \in V \text{ s.t. } P_{vu} \geq p > 0, P_{zu} = 0 \ \ \forall z \in V - \{v\} \tag{46}$$

By above formula we have:

$$\sum_{u,v \in V} P_{uv} \geq N\,p \tag{47}$$

By substituting above inequality and the result of Lemma 5 in Eq. 15 we have:

$$\begin{aligned} \mathbb{E}[\mathcal{T}] \ &\leq \ \frac{N-1}{\frac{1}{2N}\sum_{u,v\in V} P_{uv}} \left(\sum_{i=1}^{N-1} \frac{1}{(1 - P(S_u(\mathcal{T}_i) \equiv S_v(\mathcal{T}_i)))} + N \right) \\ &\leq \ \frac{N-1}{\frac{p}{2}} (N\beta + N) = \frac{2}{p}(N-1)N(1+\beta). \end{aligned} \tag{48}$$

Therefore, in this case time is of order $O(N^2)$.